

## Power Meters

### Power measurements

A power meter relays the measured amount of power to the Solar-Log™ for analysis. If you wish to consume the self-produced power from a PV plant, the meter serves as a consumption meter, displaying a comparison of the power produced and consumed. The meter can be configured to operate with the Solar-Log™ in three different modes:



1. Measuring power consumption for the optimal utilization of self-produced power.
2. Measuring the total amount of power that has been fed into the grid.
3. Measuring the power production from inverters that are not directly supported by Solar-Log™.

Technical data	Solar-Log™ PRO380-Mod three-phase current meter, MID (calibrated), RS485	Solar-Log™ PRO380-CT, Transformer-connected meter, RS485, three-phase	Iskra uncalibrated, 1-phase, S <sub>0</sub>	Iskra uncalibrated, 3-phase, S <sub>0</sub>
Connections	External tariff switching/ 4-pin S <sub>0</sub> Out for A+, A- / 2-pin Modbus interface	2 x S <sub>0</sub> (forward, reverse) RS485 (Modbus) External tariff switching	6-pin S <sub>0</sub> -In / Out connector / max. cable length 10 m	
Direct connection	100 A	6 A (Transformer input)	80 A	65 A
Interfaces	S <sub>0</sub> /RS485 max. 32 units	S <sub>0</sub> /RS485	S <sub>0</sub>	S <sub>0</sub>
Voltage U <sub>n</sub>	3 x 230/400V AC (-15% - +10%)	3 x 230 / 400 V AC (100/173V - 270/468V)	230 V -20% - +15%	3 x 230 V / 400 V -20% - +15%
Measuring range	20 mA - 100 A	6 mA - 5 A	4 mA - 80 A	4 mA - 65 A
Self-consumption	< 10 VA - < 2 W per phase	≤ 2 W per phase - ≤ 10VA per phase	< 8 VA	< 6 VA
Start-up current	20 mA	3 mA	20 mA	20 mA
Power frequency	50Hz (+10%)	45 - 60 Hz	50 Hz / 60 Hz	50 Hz / 60 Hz
Dimensions (w x h x d) in mm	70 x 140 x 63	70 x 140 x 63	36,5 x 100,5 x 65	65,11 x 84,25 x 53,57
Wire diameter	25 mm <sup>2</sup>	Max. 10mm <sup>2</sup> or 2,5mm <sup>2</sup> (Additional terminals)	2,5 - 10 mm <sup>2</sup>	2,5 - 16 mm <sup>2</sup>
Protection level	IP51	IP51	IP20	IP20
LCD display	6 + 2 Digits	5 + 3 Digits	2 x 7-digit-LCD	6+1 digit, 100 Wh resolution
S <sub>0</sub> pulse	1000 p / kWh	10000 Imp/kWh, 30 ms	1000 p / kWh	500 p / kWh
Misc.	Blue illuminated display One additional re- settable counter Display for active and reac- tive power consumption in two energy flow directions Display: I, U, P, S, F, cos phi	Blue illuminated display One additional re- settable counter Display for active and reac- tive power consumption in two energy flow directions Display: I, U, P, S, F, cos phi	2 counters: 1x total, 1x resettable	no LCD display
Warranty	2 years	2 years	1 year	1 year
Article number	255913	256059	255346	255347

## Article number

Solar-Log™ PRO380-CT 500A Measuring transformer for conductor line 30 x 10 mm or compact round cable up to 26 mm Class 1, non calibrated	256067
Solar-Log™ PRO380-CT 250A Measuring transformer for conductor line 30 x 10 mm or compact round cable up to 26 mm Class 1, non calibrated	256068
Solar-Log™ PRO380-CT 100A Measuring transformer for conductor line 30 x 10 mm or compact round cable up to 26 mm Class 1, non calibrated	256069
Solar-Log™ PRO380-CT 500A Cable split core current transformer Class 1, round cable up to 32 mm, non calibrated , small size model, connecting cable 2,5 m included	256070
Solar-Log™ PRO380-CT 250A Cable split core current transformer Class 3, round cable up to 18 mm, non calibrated , small size model, connecting cable 2,5 m included	256071
Solar-Log™ PRO380-CT 100A Cable split core current transformer Class 3, round cable up to 18 mm, non calibrated , small size model, connecting cable 2,5 m included	256072
Solar-Log™ PRO380-CT 500A, Class 0,5, Measuring transformer for conductor line 30 x 10 mm or compact round cable up to 26 mm, Declaration of Conformity, approval for billing	256073
Solar-Log™ PRO380-CT 250A, Class 0,5, Measuring transformer for conductor line 30 x 10 mm or compact round cable up to 26 mm, Declaration of Conformity, approval for billing	256074
Solar-Log™ PRO380-CT 100A, Class 0,5, Measuring transformer for conductor line 30 x 10 mm or compact round cable up to 26 mm, Declaration of Conformity, approval for billing	256075



Measuring transformer



Cable split core current transformer