# solaredge

### Antenna for Wi-Fi and ZigBee Communications

SE-ANT-ZBWIFI-KIT



#### **Simple Wireless Connectivity**

- Used to connect a SolarEdge device to the monitoring platform via Wi-Fi
- Used to connect a SolarEdge device to Smart Energy devices via ZigBee communications
- Antenna external to inverter for wider range
- Wi-Fi and ZigBee stations are built into the SolarEdge device
- Indoor or outdoor usage
- 5 years warranty

## solaredge

### Antenna for WiFi and ZigBee Communications

SE-ANT-ZBWIFI-KIT

COMPATIBLE INVERTERS	SExxx-xxxxxBxxx	
ELECTRICAL SPECIFICATIONS		UNIT
Frequency Range	2.4-2.5	GHz
Gain (Max)	5	dBi
Beam Width – Horizontal	360	Degrees
Beam Width – Vertical	50	Degrees
Aaximum Input Power	5	W
nput Impedance	50	Ohm
/SWR	2.1:1	
Polarization	Linear	
mpedance	50	Ohm
Radiation	Omni Directional	
Antenna Type	Co-linear Dipole	
Antenna Design	Dipole Array	
Application	Indoor\Outdoor	
ENVIRONMENTAL SPECIFICATIONS		
Operating Temperature	-40 to +140/ -40 to +60	°F/ °C
Storage Humidity	10% to 90% non-condensing	
MECHANICAL SPECIFICATIONS		
Dimension (Height x Diameter)	8.7x0.5/222x13	In / mm
Veight	0.11/50	lbs / gr
Cable	RG174	
Cable length (Max)	53/ 135	In / cm
Connector	RP SMA	
nternal Material	PCB + spring	
Base Material	PC Lexan 503R-WH5151L or	
	WH8G952 Sabic	

\* Product is shipped 5 devices in a box

© SolarEdge Technologies, Inc. All rights reserved. SOLAREDGE, the SolarEdge logo, OPTIMIZED BY SOLAREDGE are trademarks or registered trademarks of SolarEdge Technologies, Inc. All other trademarks mentioned herein are trademarks of their respective owners. Date: 06/2018/V01/ENG ROW. Subject to change without notice.